

問題：如何變更 Kodak i1220 scanner 掃描器驅動程式介面成爲中文操作介面

原因：Kodak i1220 scanner 掃描器驅動程式介面預設值爲英文

解法：增加 DefaultLanguage=L_CH_TWN 於

C:/WINDOWS/Twain_32/Kodak/kds_i1200 目錄下的 const. 檔案(組態設定值)中.

Const 檔內容如下：

; Copyright (c) 1998-2006 Eastman Kodak Company, All Rights Reserved

;

; This file is only for the use of Eastman Kodak Company, altering

; the information in this file is not authorized, except with its

; express consent.

[dsIdentity]

; kds.log bit values, add together as needed (ex: 1+2+4=7)

; 0 - debug off (use this normally)

; 1 - debug on (full logging, deletes kds.log first)

; 2 - preserve kds.log (set to 3 if you want full logging)

; 4 - flush to disk (use for crashes, runs slow, usually use 7)

; 16 - WIRE trace (usually use by itself)

; 64 - memory trace (usually use by itself)

; 256 - database dump (usually use by itself)

;

; If Debug is set in the range 1-7, you can also set DebugFilter to:

; - no filtering (use this normally)

; TWAIN - log communication between application and driver

; WIRE - log communication between driver and scanner

Debug=0

DebugFilter=

; The simulator immitates the behavior of a physical scanner, it is

; for the use of integrators. Use your model name (ex: i1320) to

; turn it on, leave it empty or set it to zero (0) to turn it off.

Simulate=0

DefaultLanguage=L_CH_TWN ←增加此行，將內定語言設爲繁體中文